

access

LIGHTING

Read & Save these Instructions Models: 50071/50072/50073 Installations & Operation Instructions

1) TOOLS AND MATERIALS REQUIRED

- ❖ Blade Screwdriver
- ❖ Star Screwdriver
- ❖ Wire Cutters
- ❖ Wiring supplies as required by Electrical Code

Attention:

Before assembling your lighting fixture, please read the following instructions.

(2) GENERAL

1. To ensure the success of the installation, be sure to read these instructions thoroughly before beginning.
2. All electrical connections must be in accordance with local codes, ordinances, or the National Electrical Code. If you are unfamiliar with methods of installing electrical wiring, secure the services of a qualified licensed electrician.
3. These fixtures are intended for mounting to a standard 4" x 2 ¼" deep metal octagon outlet box. The box must be directly supported by the building structure.
4. Before commencing with the installation, **disconnect the power by turning off the circuit breaker** or by removing the fuse at the fuse box. Turning the power off using the light switch is not sufficient to prevent electrical shock.

NOTE:

The important safeguards and instructions appearing in this manual are not meant to cover all possible conditions and situations that may occur. It must be understood that common sense, caution and care, are factors that cannot be built into any product. The person(s) caring for and operating the fixture must supply these factors.

(3) UNPACKING THE FIXTURE

On checking the contents of the box you will find;

1. Fixture assembly
2. Glass Shade
3. Halogen Bulb
4. Tempered Glass Bulb Cover
5. Mounting Hardware Pack

(4) PREPARE THE FIXTURE

1. If you are replacing an existing fixture, disconnect and remove the old fixture. Expose the supply wiring from the outlet box.
2. Lay the un-assembled fixture on a soft surface and carefully remove all the packing material.
3. Remove the three Knurled Knobs located on the rear of the fixture to separate the two-ring assembly. (a)
4. Remove the protective cardboard inserts and unscrew the three retaining spacers (b) located on the surface of the two-ring assembly and remove the top ring.
5. Insert the supplied glass diffuser over the bottom ring, with the dome of the glass shade pointing down and re-attach the top ring. Secure with the three retaining spacers.
6. Though supplied, these fixtures do not require the use of a cross bar for attaching them to a junction box and the fixtures have been designed to be attached directly to a standard junction box
7. Attach the supply wires from the junction box to the fixture wires. The Black supply wire attaches to the Black fixture wire and the White supply wire attaches to the White fixture wire. Secure these connections with supplied wire nuts and tape these connections with electrical tape.
8. Attach the fixture to the junction box with screws as supplied
9. Insert **Halogen bulb** between sockets. **Do Not Touch the Halogen Bulb with Bare Hands Use a Soft Dry Cloth.** Fit the supplied **tempered glass cover** over the bulb using the supplied glass clips.
10. Attach the two ring assembly to the base of the fixture and secure with the three Knurled Knobs
11. Restore electricity and enjoy your new lighting fixture.

CAUTION:

- **Ensure that the Fitting is Cool and Switched off, Before Changing Bulbs.**
- **Do Not use Bulbs Exceeding Maximum Wattage, As Per Caution Label.**
- **Do Not Touch the fixture whilst it is in operation.**

Lamping:

Model 50071: 1Lt x 100w R7s J-78

Models 50072/ 73: 1Lt x 150w R7s J-118

access

L I G H T I N G

Read & Save these Instructions Models: 50071/50072/50073 Installations & Operation Instructions

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT & THE HAZARDS INVOLVED. CONSULT A QUALIFIED ELECTRICIAN TO ENSURE CORRECT BRANCH CIRCUIT CONDUCTOR.

