



## Digital Multimeter, Auto-Ranging, 1000V



This automatically ranging digital multimeter that measures AC/DC voltage, AC/DC current, and resistance. It can also measure temperature, capacitance, frequency, duty-cycle, test diodes and continuity. Exclusively designed from the ground up by electricians for electricians. Years of field research, combined with extensive input from electricians across America, inspired the development of meters loaded with innovative, time-saving features.

### Specifications

<b>Batteries:</b>	2 x AAA	<b>Drop Protection:</b>	6.6' (2 m)
<b>Display:</b>	4000 Count LCD	<b>Functions:</b>	Measures up to 1000V AC/DC voltage, 10A AC/DC current and 40M $\Omega$ resistance plus temperature, capacitance, frequency, duty-cycle, test diodes and continuity
<b>Voltage:</b>	1000V AC; 1000 V DC	<b>Frequency:</b>	1Hz - 500 KHz
<b>Current:</b>	10A AC; 10A DC	<b>Capacitance:</b>	1000 $\mu$ F
<b>Ohms (Resistance):</b>	40M $\Omega$	<b>Ingress Protection:</b>	IP42
<b>Standard:</b>	CAT IV 600V / CAT III 1000V	<b>Temperature Range:</b>	0 $^{\circ}$ - 1000 $^{\circ}$ F (-18 $^{\circ}$ - 538 $^{\circ}$ C)
<b>Included:</b>	Carrying Case, Test Leads, Thermocouple, and Batteries	<b>Overall Length:</b>	7" (17.8 cm)
<b>Overall Height:</b>	2.09" (5.3 cm)	<b>Overall Width:</b>	3.55" (9 cm)
<b>Weight:</b>	14.4 oz (408 g)		